SPECIFICATIONS

	Colour	Silver
TWY31 INSTASHARE BUTTON	Wireless Transmission Frame Rate	Up to 60 fps depending on environment (1080P60 / 4K30P)
	TX Button Input Resolution	Up to 4K30P
	Audio Rate	Stereo, radio quality 16bits 48KHz
	Wi-Fi Standard	IEEE 802.11ac 5GHz, 2T2R MIMO
	Authentication Protocol	Wi-Fi standard
	Wireless Security (Encryption)	WPA2/3 Personal / WPA2 Enterprise, support AES-256
	Wireless Coverage Reach	Max. 15 m (Between the button and the display)
	Cable	USB Type-C
	Power Supply	DC 5V±10%, minimum 0.9A
	Power Consumption	Max 4.5W
	Dimension (WxHxD)	67mm x 67mm x 23.2mm
	Temperature Range	Operating: 0°C to +40°C. Storage: -10°C to +60°C
	Humidity Range	Operating: 10% to 80% relative humidity Storage: 5% to 90% relative humidity (non-condensing)
	Compatibility	1. RM03 series (with USB Type-C). 2. RP02, RE01, RM02K, RM02S, CP01K, CS01, SL02K series, and VC01A (with USB Type-C to USB Type-A adapter)
TDY31 WIRELESS USB DONGLE	Color	Black
	Wi-Fi Standard	802.11 a / b / g / n / ac
	Interface	USB 3.0
	Wi-Fi Band	Dual Band 2.4GHz / 5GHz
	MU-MIMO	Yes
	Wi-Fi Performance	2.4 GHz: up to 400 Mbps, 5 GHz: up to 867 Mbps
	External Antenna	2
	Supported OS	Android™
	Wireless Coverage Reach	Max. 15 m (between dongle and display)
	Security	WPA-PSK / WPA2-PSK / WPA / WPA2 / WEP
	Power Supply	DC 5V, 0.9A maximum
	Dimension (WxHxD)	12 mm x 41mm x 137mm
	Net Weight	0.055kg
	Temperature Range	Operation: 0° to +40°. Storage : -40°~70°
	Humidity Range	Operation: 10% to 90%. Storage: 5% to 90%
	Compatibility	RM03, RP02, RE01, RM02K, RM02S, CP01K, CS01, SL02K, ST02, ST02S, IL01, BH01, BH01T, BH01N, BH01D series, and VC01A
TCY31 INSTASHARE DOCK	Colour	Black
	Weight (Net)	420g
	Dimension (WxHxD)	106mm x 85mm x 150mm
	InstaShare Button Loading Quantity	4 pcs
	Product Material	PC+ABS & aluminum alloy 6063 & silica gel

BenQ Europe B.V.

Meerenakkerweg 1-17, 5652 AR Eindhoven, The Netherlands BenQ Austria GmbH Central & Eastern Europe Altmannsdorfer Strasse 89 T BenQ Deutschland GmbH Essener Straße 5 46047 Oberhausen

and GmbH BenQ Deutschland GmbH
46047 Niederlassung Österreich
Wehlistraße 27b / Stg. 2 /
Top 5, 1200 Vienna

Austria +43-190-7276-0 Zweigniederlassung Baden Täfernstrasse 32 5045 Baden-Dättwil Switzerland +41-44-74399-99 BenQ Benelux B.V.

Meerenakkerweg 1-17, 5652 AR Eindhoven The Netherlands +31-88-888-9200

BenQ Nordic AB

Box 1072 (Norgegatan 1) 16432 Kista, Sweden +46-8-588-98-804 BenQ UK Ltd.3
Staplehurst Office Centre

Weston-on-the-Green, Bicester OX25 3QU United Kingdom +44-870-850-4417 Viale E. Marelli, 165 20099 Sesto San Giovanni (MI) Italy +39-02-3664-3740

BenQ Italy S.r.I

lli, 165 La Boursidière RN186 92357
San Giovanni (MI) Le Plessis-Robinson
France
-3740 +33-0-1-7037-1717

Calle Constitucion, 3 (2-1) 08960 Sant Just Desvern Spain BenQ Europe B.V.

Representative Office in Russia Park Place Moscow, 113/1 Leninsky, Prospekt B-101, 117198 Moscow, Russia +7-095-937-8532



© 2022 BenQ Corp. Specification may vary by region, please visit your local stores for details. Actual product's features and specifications are subject to change without notice. This material may include corporate names and trademarks of third parties, which are the properties of the third parties respectively.



Benq

Share great ideas with a single click



TZY31 INSTASHARE BUTTON SOLUTION

One-click wireless screen sharing

Get ready to welcome a new generation of meetings where you are free to move around and share content without limits. Whether it is to share details with the room or start video conferencing on the large screen, the InstaShare Button Solution eliminates the fuss of passing around cables, so everyone can focus on what is important - your ideas.



SEAMLESS CONTENT SHARING FOR ALL NOTEBOOKS

Wirelessly share content with everyone in the meeting, no matter what notebook you're using. The InstaShare Button Solution is compatible with Windows[®], macOS^{*}, and Chrome[®] OS laptops.

CONVENIENT CONNECTIVITY

The USB Type-C connector enables a one-cable plugand-play solution that works seamlessly with Windows notebooks, MacBooks* and Chromebook®. Just plug the InstaShare Button in and start sharing content with a single click.

GET EVERYONE INVOLVE

Enhance productivity with a side-by-side view of everyone's contributions. The InstaShare Button Solution works with InstaShare 2, a wireless screen sharing software that lets up to nine devices cast content simultaneously on your BenQ display.

* is a trademark of Apple Inc.

CAST VIDEO CALLS FROM YOUR NOTEBOOK TO ANY DISPLAY

Start a video call from your notebook and mirror it instantly to any BenQ display. With the display's external camera and powerful built-in speakers, you ensure that everyone in the meeting room can be seen and heard clearly, from every corner of the room.

COMPLETE CONTROL WITH A SIMPLE TOUCH

Enhance collaboration with seamless content sharing. The InstaShare Button allows you to cast personal device screens onto the BenQ display to let all meeting's attendees see. With a simple touch, users can also control shared devices right from the display.

INDUSTRY-LEADING CONNECTION QUALITY

Enjoy smooth meetings without disruptions. The InstaShare Button Solution features industry-leading connection quality to ensure stable screen sharing, no matter where you sit in the room.

SHARE CONTENT YOUR WAY

Easily switch between casting your entire screen or customising the content you show. With the InstaShare Button Solution, you can opt to share photos, videos, audio, or your camera feed for flexible discussions without interruptions.











SCREEN

CAMERA

PHO.

PHOTO

/IDEO

MICROPHON

